

A MIDI Footcontroller For Gigs With Audio Plugin Hosts

Helmut Keller

This paper describes a MIDI foot controller for gigs with audio plugin hosts. The foot controller should enable a musician to control a computer running an audio plugin host during a live performance. Thus the foot controller should visualize the controlled host properties like: name of the selected song, the selected song part, the states of switches and the values of knobs. The display of an activated tuner should be shown on the footcontroller as well. There is no commercial product available that satisfies all requirements. Thus the author decided to use the hardware of an available footcontroller (the MIDI Captain from Paint Audio) and write a firmware with the desired features by himself. The MIDI Captain is a good choice because its hardware is capable enough and its firmware is written in the user friendly language Circuit Python. The firmware can be easily exchanged on the USB drive of the MIDI Captain.

1. Introduction

The author is using Windows computers for the processing of his guitar sound at live performances since more than 15 years. At that time he used the software Guitar Rig 5 from Native Instruments and the associated audio interface and foot controller named Rig Kontrol 3. About 5 years later he moved to a hardware solution: the Helix floor board from Line 6. The sound quality and playing experience of the Helix amp simulations was however still not satisfying. Thus a step back to a software solution with Gig Performer as the audio plugin host for live performances, the Baby Face FS Pro from RME as the audio interface and the iRig Blue Board from IK Multimedia as the footcontroller followed soon. Since every available audio plugin can be used the achievable sound quality and playing experience is always state of the art.

The foot controller of this setup has only 4 switches and two expression pedal inputs. Thus the amount of controllable parameters is very limited. This could be managed somehow. The main problem is that there are only 4 LEDs for feedback from the host. This is not enough to visualize which song and song part is currently selected. A tuner display is barely possible with 4 LEDs too. Thus it is necessary that the musician can have a look on the screen of the computer during his performance. With a foot controller providing more switches, LEDs and a display it could be possible to hide the computer and audio interface at a save place somewhere on or behind the stage. This would result in a much more reliable setup.

There are some commercial MIDI foot controllers available with more switches, LEDs and one or even more displays but not all of them accept feedback from the host and none of them can show a graphical tuner display. The author selected the MIDI Captain from Paint Audio for his improved setup because its hardware resources are sufficient. The missing features namely visualizing incoming MIDI data and displaying tuner values have to be implemented in a custom firmware written by the author himself.

The firmware of the MIDI Captain is written in the user friendly language Circuit Python and it can be easily exchanged on the USB drive of the device. There are a few examples of Circuit Python code for the MIDI Captain available on GitHub too. Thus this project seems to be a doable task.

2. The hardware of the MIDI Captain

The MIDI Captain STD provides ten foot switches. A LED ring with three color LEDs is placed around each switch. The RGB values of the color of each LED can be set separately.

Four switches named 1, 2, 3 and 4 build an upper row on the top panel. Four switches named A, B, C and D build a lower row and two switches labeled with symbols for up and down build a column at the right side of the top panel.

Left from the center of the top panel there is a small quadratic color display with 240 x 240 pixels and a size of 29 x 29 mm. This is not very big, but a song name and tuner data can be shown in a still readable size for a person standing close to the footcontroller. The remaining important states can be visualized with the help of the ten LED rings. Right from the display there is a rotary encoder with 32 steps per cycle and an integrated push button switch.

On the rear panel we can find an On/Off-switch, a USB type B connector, a 9V power supply input, two 5 pin connectors for MIDI output and input and two 6.3 mm TRS inputs for the expression pedals EXP1 and EXP2.

Unfortunately Paint Audio uses a special wiring for the expression pedal inputs. The tip carries a fixed DC voltage of 3.3 V and the ring is connected to the analog input. There are no pull up resistor between tip and ring. This means that we need adapter cables with exchanged tip and ring for many expression pedals and external foot switches. For external switches a pull up resistor is highly recommend to avoid very slow switching times from the closed to the open state.

On the right side of the device there is a lid to access two replaceable batteries of size AA.



Fig. 1: The MIDI Captain STD

The device can be powered by USB, a 9V power supply or the batteries at the same time. NiMH batteries can be charged inside the device. Full charge is reached after about 12 hours of internal charging. The device operates about 8 hours with fully charged batteries.

Via USB the MIDI Captain exposes a bidirectional MIDI Interface. When switched on while footswitch 1 is pressed the USB drive of the MIDI captain is available on a connected computer.

The MIDI interface with the 5 pin connectors can be used independently from the USB MIDI interface.

Beside the original MIDI Captain STD shown in **Fig. 1** there are two newer versions named Blue and Gold. Both new versions provides a third bidirectional MIDI interface in a specific wireless format which is only used by devices from Paint Audio. There are versions with less foot switches and no expression pedal inputs too. The author's firmware requires one of the three versions with ten footswitches.

3. Programming the firmware of the MIDI Captain

This chapter can be skipped by those who don't want to modify the author's firmware.

Paint Audio provides several versions of firmware for the MIDI Captain. Unfortunately none of them is useful for our purposes. The only version which allows feedback from the host device works with Kemper products only. The Circuit Python code of the original firmware versions is stored in already compiled files and is thus not readable.

Fortunately there is a GitHub project [1] where the access to the MIDI Captain's hardware resources is explained with readable Circuit Python script examples. The GitHub project [2] is an example for bidirectional communication with Kemper products. Another example [3] for Kemper products exists, but it is very hard to understand. A good introduction into Circuit Python is [4]. There you will find an introduction to the Mu Editor too. The Mu Editor is the preferred tool to edit and debug Circuit Python scripts. You can download the Mu Editor from [5] free of charge.

The first step of writing new firmware is to store the original firmware. You have to keep footswitch 1 pressed while switching on the MIDI Captain. Its USB drive is then available as "MIDICAPTAIN" on a connected host computer. Copy the complete content of the USB drive and save it at a safe place. Don't forget to eject the USB drive before you disconnect the MIDI Captain from the host computer.

At least now you should install the Mu Editor on your computer.

The next step is to modify the file `boot.py` on the USB drive of the MIDI Captain with the Mu Editor. You have to change the following two lines:

```
import supervisor
supervisor.disable_autoreload()

into:
```

```
# import supervisor  
# supervisor.disable_autoreload()
```

This deactivates the two lines and enables automatic re-booting when a file on the USB drive of the MIDI Captain has been changed.

Now you should inspect the file `code.py` on the USB drive of the MIDI Captain. You will recognize that this script imports different files with the extension “.mpy” depending on which footswitch is pressed during switching on. These files are compiled Circuit Python scripts and contain the different versions of the firmware from Paint Audio. When you overwrite the original file “code.py” with the file “code.py” from the author [6] you have installed the authors firmware. It will however not run without errors because three files with the extension “.pcf “ are missing. These are files containing three fonts used by the author but not by Paint Audio. After copying the three font files from [6] to the “fonts” directory of MIDI Captain’s USB drive the authors firmware is ready to go and you can be modify it. The author’s code is not very complicated and explained by comments.

4. Installing an deinstalling the author’s firmware

Before you install the author’s firmware you should safely store the original firmware: Keep MIDI Captain ‘s footswitch 1 pressed while switching on. MIDI Captain’s USB drive is then available as “MIDICAPTAIN” on a connected host computer. Copy the complete content of the USB drive and save it to a save place.

You can download the author’s firmware package from [6]. It is free of charge.

Overwrite the original file “code.py” on the USB drive with the file “code.py” from [6].

Copy the following three files “PTSans-Bold-60.pcf”, “PTSans-NarrowBold-54.pcf” and “PTSans-Regular-20.pcf” from [6] into the directory “fonts” on the USB drive:

Copy the file “HKAudioSetup.txt” from [6] into the directory “setup” on the USB drive.

Eject the USB drive before you disconnect the MIDI Captain from the host computer.

Switch the MIDI Captain off and on to activate the author’s firmware.

To deinstall the author’s firmware just overwrite the author’s file “code.py” with the original file.

If some problems should occur just delete the complete content on MIDI Captain’s USB drive and write back the complete content you have saved at the very beginning of the installation process.

5. User manual of the author’s firmware

All physical MIDI Captain controls are mapped to MIDI control change numbers (CC#s). The mapping is shown in **Table 1**.

This mapping is compatible with the iRig Blue Board for the two expression pedal inputs and the foot switches A to D. Thus associated functions can be used with both controllers.

The control change commands are send by MIDI captain whenever a value of a physical control has changed. The switches send a value of 127 when pressed and a value of zero when released.

The authors firmware reacts on received control changes commands with the same numbers too. For all controls except the up and down footswitches the received value is shown on an associated small rectangle on the display of the device. The surrounding LED rings of all ten footswitches are set fully bright for values > 63 and are dimmed for lower values.

Table 1: The mapping of control change numbers to the MIDI Captain controls.

CC#	MIDI Captain Control
11	Rotary encoder
12	Expression pedal input EXP1
13	Expression pedal input EXP2
14	Encoder's push button switch
15	Footswitch 1
16	Footswitch 2
17	Footswitch 3
18	Footswitch 4
19	Footswitch Up
20	Footswitch A
21	Footswitch B
22	Footswitch C
23	Footswitch D
24	Footswitch Down

The CC#25 has a special meaning: When send by the host with a value > 63 the MIDI Captain is set into a “tuner mode”. The “normal mode” is set by smaller values.



Fig. 2: The display layout of the author' firmware

The display layout of the author's firmware is shown in **Fig. 2**. It is organized in 5 rows with rectangles related to the received CC#s. A received song or preset name and the MIDI Captain's battery voltage are displayed too:

1. CC#12 and CC#13
2. CC#15, CC#16, CC#17 and CC#18.
3. A song or preset name, or when in tuner mode the note name and a pointer representing the pitch deviation.
4. CC#20, CC#21, CC#22 and CC#23.
5. Battery voltage, CC#14 and CC#11

The received values for each CC# are shown as a bright bars over a darker background. Remember that values of the CC#s mapped to the ten footswitches are shown by the associated LED rings too. The values of CC#19 and CC#24 are only shown by the associated LEDs because there are no associated rectangles on the display.

The default colors and names of CC#11 to CC#24 are read from the file HKAudioSetup .txt. The author's file has this content:

```
CC#11: 4, Master
CC#12: 2, Position
CC#13: 2, Mode
CC#14: 4, Def.
CC#15: 16, Play
CC#16: 16, Loop
CC#17: 10, Tap
CC#18: 12, Tune
CC#19: 7, Up
CC#20: 8, SP 1
CC#21: 8, SP 2
CC#22: 8, SP 3
CC#23: 8, SP 4
CC#24: 7, Down
```

The number after “CC#” is the control change number of the control. The number after “:” is the color index of the associated LED or rectangle. See **Table 2** for the color names of the color indices. The text after the “,” is the name displayed in the associated rectangles. Please realize that there is a blank after the comma. The name should describe the function of the control. The names for CC#19 and CC#24 are ignored because there are no associated rectangles on the display.

Table 2: The color index table

Color Index	Color Name	Color Index	Color Name
0	black	14	cyan
1	dark red	15	azure
2	dark yellow	16	blue
3	dark green	17	violet
4	dark cyan	18	magenta
5	dark blue	19	purple
6	dark magenta	20	pastel red
7	grey	21	pastel yellow
8	red	22	pastel green
9	orange	23	pastel cyan
10	yellow	24	pastel blue
11	lime	25	pastel magenta
12	green	26	white
13	spring		

The user can edit this file to define his own default colors and names. During operation the colors and names can be set by MIDI system exclusive commands too.

The MIDI Captain reacts on MIDI system exclusive commands in the following format shown as hex-strings:

F0, 59, “CC#”, “Color Index”, “Name String”, F7

The bytes F0 and F7 mark the start and the end of a system exclusive command. The byte 59 is the manufacturer ID expected by the authors firmware.

“CC#” is the hex-string of the control change number. “Color Index” is the hex-string of the color index of the associated LEDs and display rectangles. The “Name String” contains the hex-string values of the ASCII-characters of the name. Null termination is not expected at the end of the string. The names for CC#19 and CC#24 are ignored because there are no associated rectangles on the display.

The CC#25 has a special meaning again. It sets the name displayed in the big rectangle in center of the display. This name is probably a song or preset name. The authors firmware breaks the text into two lines if too long for one line. It truncates the text too, if too long at all. Sending strings longer than 22 characters makes no sense.




Fig. 3: The display layout of the author's firmware in tuner mode

In tuner mode the big rectangle in the center of the display shows the note name and the pitch deviation as a pointer (see **Fig. 3**).

The MIDI note number is received via note on and note off commands. The MIDI note number is translated by the author's firmware to the proper note name. Note off means that no pitch deviation can be detected any more. This is shown as the special note name "-----".

The pitch deviation is received via pitch wheel commands. A value of 8192 corresponds with 200 cents. The pitch deviation is limited by the firmware to + / - 29 cents and then displayed as a pitch deviation pointer.

The free plugin MTuner from Melda Productions sends the tuner data with the expected MIDI commands.

The author's firmware utilizes the USB and 5 pin connector MIDI interfaces at the same time. It sends all commands to both outputs and listens to commands on both inputs.

6. The Bluetooth LE connection to the host computer

A wireless connection between the MIDI Captain and the host computer is necessary because the maximal length of USB cables is too short and two long cables for the 5 pin MIDI input and output would be very uncomfortable.

The MIDI Captain's Blue and Gold versions provide a bidirectional wireless MIDI interface. However it is only compatible with a counterpart from Paint Audio which requires 5 pin MIDI connectors for input and output at the host computer side. There is no information available how to access this interface in firmware. Thus the MIDI Captain's wireless MIDI interface can't be used by the author's firmware.

The setup of the author uses a MIDI over Bluetooth LE connection between the MIDI Captain and the host computer. On the MIDI Captain a WIDI Master from CME is plugged into the two 5 pin MIDI connectors. The power is supplied by the MIDI output connector of the MIDI Captain. On the host computer a WIDI Bud from CME is plugged into a USB type A connector. On Macs the WIDI Bud would not be necessary because Macs support MIDI over Bluetooth LE directly.

7. An application example with Gig Performer

The author uses the audio plugin host software Gig Performer from Deskew Technologies for his live performance setup. A basic bidirectional communication with a MIDI Captain running the

authors firmware is very easy. A Gig Performer's widget is linked to a MIDI Captain's control with the widget's "MIDI learn"-function: You just need to change the value of the physical control to establish the link. If you want that the widget values are displayed on the MIDI Captain too, you just need to enable the "Sync"-function of the widget. Then each time the widget value has changed it is send to the MIDI Captain with the associated CC# too.

It is not possible to change the MIDI Captain's colors and names in an easy way. For this purpose the Gig Performer has to send the appropriate MIDI system exclusive commands to the MIDI Captain. Fortunately we can achieve this behavior by writing a script for the Gig Performer's global rackspace. The scripts for Gig Performer use a very user friendly language and are not difficult to write and understand.

Fig. 4 shows a screen shot of Gig Performer in "Set List View" as used in the author's setup during live performances.

The name of the current song is shown in big letters in the second line of the screen. The previous and next song can be selected by clicking left or right from the current song name. You can select songs in the setlist at the left side of the screen too.

With the help of MIDI Captain's up and down footswitches you can select songs in the current setlist too. A short press selects the previous or next song, a long press selects the first or last song in the setlist. If both switches are pressed the song in the middle of the setlist is selected. The author's script sends the current song name to the MIDI Captain too.

The song parts appear below the song name. You can select them by clicking on them.

With the help of the MIDI Captain's footswitches A, B, C and D you can select the song parts too. If there are less than four song parts within a song the color of the associated MIDI Captain switches is black and the name is empty. The color of controls associated with existing song parts is red and the name is the song part's name. This way the musician can see the available song parts on the MIDI Captain too.

Gig Performer always selects the song part number one when a new song is selected. The author however assorts his song parts by increasing gain and volume and sometimes he wants to start a song with a high gain sound. The author's script implements this feature by "abusing" the transpose property of Gig Performer songs.

The rack space below the song part selector contains all widgets that control parameters of the underlying audio plugin setup. All widget values are stored with the selected song part by clicking the "Snapshot"- button. These values are recalled when the same song part is selected again

The expression pedals inputs EXP1 and EX2 of the MIDI Captain are connected with an expression pedal with a toe switch. They are linked to the widgets named "Position" and "Wah" which control an audio plugin emulating a Volume- and a Wah-Wah-pedal.

Below the local rackspace there is the global rackspace. Widget values of this rackspace do not change when another song or song part is selected.



Fig. 4: A screen shot of the VST host Gig Performer as used in the author’s setup

The four rectangular buttons on the global rackspace are linked to MIDI Captain’s footswitches 1, 2, 3 and 4.

The “Play”- and “Loop”-buttons control Gig Performer’s streaming audio file player. The authors uses the audio file player not during performances but or practicing only. For each song the appropriate audio file is loaded by the script. A loop is defined for each audio file too. This loop contains the section of the song which needs the most amount of practicing.

The “Tap”-button can be used to tap in the tempo manually, This will temporally overwrite the tempo of the selected song. With the yellow LED-widget above the tap button you can enable a visual metronome. A yellow label on Gig Performer’s screen and the LED of MIDI Captain’s footswitch 3 will then blink in the current tempo.

The tuner button opens and activates the tuner plugin MTuner. The script additionally mutes the input signal and sets the MIDI Captain and the global rackspace into tuner mode.

The widget named “Master” controls the master volume of the setup and is linked to the rotary encoder of the MIDI Captain. A press on the encoder’s push button switch sets the master volume to its default value.

Gig Performer’s timer tick period has a length of about every 100 ms. The script sends a single MIDI command to update the state of the MIDI Captain on every timer tick. Each time another one

from an endless repeating sequence: the system exclusive commands for the song name and the switches A to D, the control change commands for all MIDI Captain controls expect the up and down foot switches, the footswitch 3 and the encoder's push button switch. Thus all relevant states are updated periodically. Note that the values of the controls are updated immediately after they have changed too, while the colors and names are updated periodically only. When the tuner is enabled the periodic update commands and the song changes by MIDI Captain's up and down footswitches are disabled. This way the MIDI Captain can react faster on the received tuner data and unintentional song changes are prevented while the song name is not displayed on the MIDI Captain.

The author's global-rackspace-script implements equalizer preset selectors for the two stereo outputs too. You can download the script file from [7].

8. Summary

Live performances of musicians with computer based signal processing are getting more and more common. If the computer and audio interface is placed at a save place on or behind the stage the reliability of such a setup is very high too. However the display of the computer may not be visible by the performing musician in this case. A MIDI footcontroller close to the performers could be used to control the setup and to show important information like the name of the selected song and the selected song part. Guitar players need to see the note name and the pitch deviation of a tuner too. Unfortunately no commercially available footcontroller is equipped with all desired features. The author's firmware for the MIDI Captain from Paint Audio implements all these features. The firmware is available free of charge and its source code is open. Together with the audio plugin host software Gig Performer from Deskew Technologies a very comfortable, flexible and reliable live setup is finally available. Of course you can use the author's firmware for bidirectional communication with other host software too, but you have to find out by yourself if it is flexible enough to meet your needs.

9. Links

- [1] Circuit Python code to access the MIDI Captain's hardware resources:
<https://github.com/nicola-lunghi/hiper-midicaptain>
- [2] Circuit Python code for bidirectional communication with Kemper devices:
<https://github.com/gstrotmann/MidiCaptain4Kemper>
- [3] Same as [2] but hard to understand:
<https://github.com/Tunetown/PySwitch>
- [4] The starting point for learning Circuit Python:
<https://circuitpython.org/>
- [5] Download link for the Mu Editor:
<https://codewith.mu/en/download>
- [6] Download link for the author's MIDI Captain firmware package:
<https://www.helmutkelleraudio.de/downloads/e5da815b5483deef1ef02b89707f769e>
- [7] Download link for the author's Gig Performer script:
<https://www.helmutkelleraudio.de/downloads/36244a6aa3ba8ec7baea98549d2fb650>